(51) International Patent Classification⁷: G01S 5/02, H04B 7/185

(21) International Application Number: PCT/US01/29054

(22) International Filing Date:
18 September 2001 (18.09.2001)

(25) Filing Language: English

(26) Publication Language: English

(30) Priority Data:
09/666,498   18 September 2000 (18.09.2000)   US

(71) Applicant: MOTOROLA INC. [US/US]; 1303 East Agonquin Road, Schaumburg, IL 60196 (US).

(72) Inventors: KING, Thomas; 9283 South Stanley Place, Tempe, AZ 85284 (US). GEIER, George; 11364 East Appaloosa Place, Scottsdale, AZ 85259 (US). GUTOWSKI, Gerald, J.; 510 North Easy Street, Palatine, IL 60067 (US).

(74) Agents: VAAS, Randall et al.; Room AN475, 600 North US Highway 45, Libertyville, IL 60048 (US).

(81) Designated States (national): AE, AG, AL, AM, AT, AU, AZ, BA, BB, BG, BR, BY, BZ, CA, CH, CN, CO, CR, CU, CZ, DE, DK, DM, DZ, EC, EE, ES, FI, GB, GD, GE, GH, GM, HR, HU, ID, IL, IN, IS, JP, KE, KG, KP, KR, KZ, LC, LK, LR, LS, LT, LU, LV, MA, MD, MG, MK, MN, MW, MX, MZ, NO, NZ, PH, PL, PT, RO, RU, SD, SE, SG, SI, SK, SL, TJ, TM, TR, TT, TZ, UA, UG, UZ, VN, YU, ZA, ZW.

(84) Designated States (regional): ARIPO patent (GH, GM, KE, LS, MW, MZ, SD, SL, SZ, TZ, UG, ZW), Eurasian

[Continued on next page]

(54) Title: METHOD AND APPARATUS FOR CALIBRATING BASE STATION LOCATIONS AND PERCEIVED TIME BIAS OFFSETS

(57) Abstract: A flowchart (400) includes the step (402) of collecting a predetermined number of TOA measurements arriving at the assisted satellite positioning mobile station from a base station, the step of (406) simultaneously collecting a corresponding number of GPS position measurements of a position of the GPS receiver, and the step (410) of computing the base station location and/or the step (414) of computing a perceived time bias offset required for a message to travel between the base station and the mobile station using the predetermined number of TOA measurements and the predetermined number of GPS position measurements.

WO 02/23215 A1

patent (AM, AZ, BY, KG, KZ, MD, RU, TJ, TM), European patent (AT, BE, CH, CY, DE, DK, ES, FI, FR, GB, GR, IE, IT, LU, MC, NL, PT, SE, TR), OAPI patent (BF, BJ, CF, CG, CI, CM, GA, GN, GQ, GW, ML, MR, NE, SN, TD, TG).

Published:
— *with international search report*
— *entirely in electronic form (except for this front page) and available upon request from the International Bureau*

For two-letter codes and other abbreviations, refer to the "Guidance Notes on Codes and Abbreviations" appearing at the beginning of each regular issue of the PCT Gazette.

METHOD AND APPARATUS FOR CALIBRATING BASE STATION LOCATIONS AND PERCEIVED TIME BIAS OFFSETS IN AN ASSISTED GPS TRANSCEIVER

Technical Field

5   The present invention relates generally to a satellite positioning receiver, and more particularly to a Global Positioning System (GPS) receiver in an assisted GPS handset operating in conjunction with one or more cellular base stations (BSs).

Background Art

      The Global Positioning System (GPS) is a satellite-based positioning system

10   developed by the U.S. Department of Defense to give accurate positional information to a GPS receiver anywhere in the world. A properly equipped GPS receiver may therefore be used in any setting in which a positional fix is desired, and typically yields positional coordinates in three dimensions.

      GPS is enabled by a satellite orbital constellation made up of twenty-four or more

15   satellites orbiting the earth in twelve-hour orbits. The satellites are arranged in six orbital planes, each containing four satellites. The orbital planes are spaced sixty degrees apart and are inclined approximately fifty-five degrees from the equatorial plane. This constellation ensures that from four to twelve satellites will be visible at any time at any point on earth with a clear view of the sky.

20   A three-dimensional position fix may be determined if signals are being received from four or more GPS satellites. The received satellite signals each contain an identifier unique to that particular satellite. These identifier codes are commonly called Gold codes or pseudorandom noise (PRN) codes and allow a GPS receiver to discriminate between signals from different satellites. Also contained within the signals are satellite ephemeris

25   data containing information such as an orbital configuration and a satellite time. (All GPS satellite signals contain a common, synchronized GPS time.) This satellite time signal allows a GPS receiver to detect a time of receipt and therefore measure a transit time of the signal. In turn, the transit time enables a GPS receiver to determine a distance (termed a pseudorange) to the satellite. Four GPS pseudoranges allow a location on the

30   Earth's surface to be determined.

      There are many uses for portable, hand-held GPS receivers including use in an assisted GPS handset. Because of processing time constraints and incomplete satellite

coverage, handset-based GPS receivers may operate in conjunction with one or more

BSs. As described in related art, the base station (BS) can be employed to relieve GPS

receivers from certain processing duties, improve the accuracy of the resulting location

solution, and improve fix coverage in areas that are marginal for GPS signal tracking

5   (e.g., in an urban canyon or indoors). The serving BS (i.e., the BS that is responsible for

maintaining communication with the handset) can provide the mobile handset with

satellite Doppler information (U.S. Patent No. 4,445,118 to Taylor, et al.) and/or satellite

ephemeris data (U.S. Patent No. 5,365,450 to Schuchman, et al.) to reduce the time

required to acquire the GPS signals and derive a location fix within the handset. In

10   addition, differential corrections can be broadcast to GPS receivers in handsets. These

corrections, if received with minimum latency, can remove most of the error associated

with each pseudorange measurement. Finally, additional range measurements can be

derived from the arrival times associated with the transmissions of pilot signals from

each BS, which can be used to augment the GPS-only solution and provide position fixes

15   in situations where GPS cannot. One type of information that is commonly relayed in the

related art is locations of nearby BSs. BS locations may be useful to the mobile GPS

receivers to give a starting position for a positional fix and may reduce the signal search

space and therefore reduce the acquisition time for the GPS signals. A second type of

information that is commonly relayed is a time bias offset associated with each nearby

20   BS. This offset is a bias between the time maintained by the BS and GPS time.

FIG. 1 shows a related art mobile GPS receiver in a cellular handset operating in

conjunction with a single BS. Each related art cellular handset receives a transmission

from the BS containing the BS position embedded therein along with a time bias offset b.

The BS position may be expressed in Cartesian coordinates as x_{BS}, y_{BS}. A drawback of the

25   related art approach is that related art handset-based GPS receivers cannot make use of

TOA measurements from the network infrastructure and calculate a positional fix based

solely on TOA measurements until the required data (x_{BS}, y_{BS}, b) is received from the BS.

What is needed, therefore, is a method for determining BS locations and time bias

offsets in a handset-based GPS receiver without necessarily having to receive the BS

30   locations and time bias offsets from the infrastructure.

Brief Description of Drawings

FIG. 1 shows related art mobile GPS receivers operating in conjunction with a base station;

FIG. 2 illustrates a distance determination utilizing Cartesian coordinates;

5   FIG. 3 shows a typical mobile station to base station geometry illustrating that the mobile station is moving relative to the base station;

FIG. 4 shows a flowchart of a first embodiment of a method for calibrating base station locations and time bias offsets;

FIG. 5 shows a flowchart of a second embodiment of a method for calibrating base

10   station locations and time bias offsets; and

FIG. 6 shows a GPS receiver that can be used for calibrating base station locations and time bias offsets.

Disclosure of the Invention

A method for calibrating a base station (BS) location and/or perceived time bias

15   offset in a mobile station (MS) with a satellite positioning receiver, such as a GPS receiver, is provided according to a first embodiment. The method includes the steps of collecting a number of TOA measurements arriving at the MS from a BS, simultaneously collecting a corresponding number of GPS position measurements of a position of the GPS receiver, and computing the BS location and/or perceived time bias offset using the

20   collected TOA and GPS position measurements.

A method for calibrating a BS location and/or perceived time bias offset in an MS with a satellite positioning receiver, such as a GPS receiver, is provided according to a second embodiment. The method includes the steps of collecting at least three TOA measurements TOA_1, TOA_2 and TOA_3 arriving at the MS from a BS, wherein a TOA

25   measurement is capable of being expressed as $TOA_t = b' + \sqrt{[(x-x_t)^2 + (y-y_t)^2]}$, with variable b' being a perceived time bias offset as seen by the MS and (x, y) being unknown BS coordinates. The method simultaneously collects at least three GPS position measurements of a position of the GPS receiver, wherein a position measurement is denoted as x_t and y_t as a function of time. The method then subtracts a first TOA

30   measurement from two subsequent TOA measurements to create two TOA measurement differences TOA_{31} and TOA_{21} and substitutes a distance variable d_t for the unknown BS coordinates x, y in the two TOA measurement differences TOA_{31} and TOA_{21}

to produce a quadratic equation for the distance variable d_1, where the distance variable is given by $d_1 = \sqrt{[(x-x_i)^2 + (y-y_i)^2]}$. The method then solves the quadratic equation for the distance variable d_1 to obtain an estimated range d_e, solves for the unknown BS coordinates x, y using the estimated range d_e, and obtains the perceived time bias offset

5   b' by subtracting the estimated range d_e from TOA_1, TOA_2, or TOA_3.

An apparatus for calibrating a BS location is provided according to a third embodiment. The apparatus includes an MS with a satellite positioning receiver, a TOA measurement storage capable of storing a plurality of TOA measurements, a GPS receiver position fix storage capable of storing a plurality of position fixes, a BS

10   coordinates solution storage, a time bias offset storage, and a processor. The processor communicates with the satellite positioning receiver to receive signals from positioning satellites and the BS and further communicates with the TOA measurement storage, the satellite positioning receiver position fix storage, the BS coordinates solution storage, and the time bias offset storage. The processor is capable of collecting and storing TOA

15   measurements, collecting and storing a corresponding number of satellite position measurements, subtracting a first TOA measurement from subsequent TOA measurements to create TOA differences, substituting a distance variable d_1 for the unknown BS coordinates x, y in the TOA differences to produce a quadratic equation, solving the quadratic equation for the distance variable d_1 to obtain an estimated range

20   d_e, solving for the unknown BS coordinates x, y, obtaining the perceived time bias offset by subtracting the estimated range d_e from the TOA measurements, linearizing TOA equations to produce linearized TOA equations, generating a vector of measurement residuals TOA_{res}, computing a weighted least squares solution x_{sol} of the TOA equations, using the weighted least squares solution x_{sol} to assess an accuracy of the linearized TOA

25   equations, and stopping the linearizing when solution error variances of the weighted least squares solution x_{sol} become less than a solution error variance threshold.

Once the BS calibration is essentially complete, the perceived time bias offset b' as seen by the MS is periodically re-determined and associated with each MS location or BS service area. Over time, this association permits construction of a temporal map, or

30   database, of perceived time bias offsets versus position over the area served by a BS. The perceived time bias offset b' represents the time bias offset b as affected by spatial error from multipath in addition to the fixed error induced by cable delays, internal BS harnessing, software processing, clock source distribution, and other factors. This map

can be derived and maintained for many BSs by the cellular infrastructure and broadcast to other MSs (whether or not GPS-equipped) to improve their location accuracy.

FIG. 2 illustrates a distance determination utilizing Cartesian coordinates. Although Cartesian coordinates are used here, other coordinates (e.g. polar) can be used

5 to determine distance. In the figure, the distance d_1 from the MS to the BS can be determined by the formula $d_1 = \sqrt{[(x_1 - x_0)^2 + (y_1 - y_0)^2]}$. This formula assumes that the earth is locally flat over the distance between the BS and MS, an excellent approximation over the range of distances expected (i.e., less than twenty km). An MS as used herein can be a cellular handset, a vehicle-based communication transceiver, or any other type

10 of mobile radio transceiver.

FIG. 3 shows a typical MS to BS geometry having an MS with a satellite positioning receiver that is moving relative to the BS. Because of the movement of the MS, it is at position MS_1 at time $t = 1$, at position MS_2 at time $t = 2$, at position MS_3 at time $t = 3$, etc. Therefore, the distance to the BS may change, as shown by distances d_1, d_2, and

15 d_3.

FIG. 4 shows a flowchart 400 of a first embodiment of a method for calibrating BS locations and perceived time bias offsets. In step 402, MS TOA measurements are collected. The derivation of the BS coordinates x, y and the perceived time bias offset b' may be done through use of at least three received TOA measurements from the BS.

20 In use, the MS may receive multiple TOA measurements from the BS. A first derived TOA measurement is:

$$TOA_1 = b' + \sqrt{[(x - x_1)^2 + (y - y_1)^2]} \qquad (1)$$

where TOA_1 is a TOA measurement derived by the BS at a time $t = 1$, where x_t and y_t are the known GPS position fix coordinates of a mobile GPS receiver at a time t (i.e., x_1 and y_1

25 are x_t and y_t at the time $t = 1$), where b' is the unknown perceived time bias offset of the BS, and where (x, y) are the unknown BS coordinates. Equation (1) therefore represents a single equation having three unknowns.

Equation (1) is linear in the perceived time bias offset b' variable, but nonlinear in the BS coordinates x, y. Note that the TOA measurement TOA_t and the mobile GPS

30 receiver coordinates x_t, y_t are time variant.

At a later time $t = 2$, denoted by the subscript 2, a second TOA measurement is derived from the BS:

$$TOA_2 = b' + \sqrt{[(x - x_2)^2 + (y - y_2)^2]} \qquad (2)$$

5

Consideration of equations (1) and (2) provides two equations with three unknowns. Derivation of a third TOA is required to generate estimates of x, y, and b'. At yet a later time t = 3, denoted by the subscript 3, a third TOA measurement is derived from the BS:

$$TOA_3 = b' + \sqrt{[(x - x_3)^2 + (y - y_3)^2]} \qquad (3)$$

5   Note that a single perceived time bias offset term b' is used in equations (1)-(3). The change in b' due to movement of the GPS receiver is assumed sufficiently small so that b' can be assumed a constant. Once the BS location has been accurately determined and verified, this assumption can be relaxed, and the perceived time bias offset b' can be determined periodically.

10   In step 406, a corresponding number of GPS receiver position measurements are generated by the GPS receiver. These take the form of x_t and y_t, where t is the time of measurement. Therefore, as the GPS receiver moves, it generates distinct positional fixes (x_1,y_1), (x_2,y_2), and (x_3,y_3), as shown in FIG. 3 and equations (1)-(3).

In step 408, the singular geometry of the TOA measurement set is tested. This is
15   done through use of a matrix M, given as:

$$M = \begin{vmatrix} (x_3 - x_1) & (y_3 - y_1) \\ \\ (x_2 - x_1) & (y_2 - y_1) \end{vmatrix}$$

The determinant of the matrix M above (which must be nonzero to solve the equations)
20   is proportional to the area enclosed by the three MS positions.

More generally, any near singularity condition that occurs when inverting the two-dimensional matrix M is an indication that the measurement set is not sufficient to determine the position of the BS, however coarsely. If the singularity of the received TOA measurements is inadequate, the method may acquire more TOA measurements.

25   In step 410, the TOA measurements and the GPS receiver position measurements are use to compute the (unknown) BS location coordinates x, y. Note that a significant geometry change must be induced by the motion of the MS before the equations can be solved. For example, if the MS was stationary, the two resulting linear equations in x and y would be linearly dependent and so could not be solved.

30   Since computation of the BS coordinates is more difficult than the computation of the perceived time bias offset b' and involves nonlinear processing, it is addressed first. It should be understood that alternately the perceived time bias offset b' could be

6

derived first and the BS location could then be derived knowing the perceived time bias offset.

Determination of an initial solution may be performed as follows. Equation (1) may be subtracted from both equations (2) and (3), producing the TOA differences:

$$TOA_{21} = TOA_2 - TOA_1 = \sqrt{[(x - x_2)^2 + (y - y_2)^2]} - \sqrt{[(x - x_1)^2 + (y - y_1)^2]} \qquad (4)$$

$$TOA_{31} = TOA_3 - TOA_1 = \sqrt{[(x - x_3)^2 + (y - y_3)^2]} - \sqrt{[(x - x_1)^2 + (y - y_1)^2]} \qquad (5)$$

where the perceived time bias offset b′ drops out due to the subtraction. Now, the distance variable d_1 from the MS to the BS at time 1 (see FIG. 2) may be defined as:

$$d_1 = \sqrt{[(x - x_1)^2 + (y - y_1)^2]} \qquad (6)$$

The $-\sqrt{[(x - x_1)^2 + (y - y_1)^2]}$ terms at the right of equations (4) and (5) are equal to $-d_1$ by definition. Therefore, by adding $+d_1$ to both sides of equations (4) and (5), they may be rewritten as:

$$TOA_{31} + d_1 = \sqrt{[(x - x_3)^2 + (y - y_3)^2]} \qquad (7)$$

$$TOA_{21} + d_1 = \sqrt{[(x - x_2)^2 + (y - y_2)^2]} \qquad (8)$$

Squaring equations (7) and (8) results in:

$$TOA_{31}^2 + 2d_1 TOA_{31} + d_1^2 = (x - x_3)^2 + (y - y_3)^2 \qquad (9)$$

$$TOA_{21}^2 + 2d_1 TOA_{21} + d_1^2 = (x - x_2)^2 + (y - y_2)^2 \qquad (10)$$

Subtracting the term d_1^2 from both sides of equations (9) and (10) gives the desired results:

$$TOA_{31}^2 + 2d_1 TOA_{31} = -2(x_3 - x_1)x - 2(y_3 - y_1)y + k_3 - k_1 \qquad (11)$$

$$TOA_{21}^2 + 2d_1 TOA_{21} = -2(x_2 - x_1)x - 2(y_2 - y_1)y + k_2 - k_1 \qquad (12)$$

where

$$k_1 = x_1^2 + y_1^2$$
$$k_2 = x_2^2 + y_2^2$$
$$k_3 = x_3^2 + y_3^2$$

Equations (11) and (12) represent two linear equations, which can be solved for x and y in terms of the unknown distance variable d_1 (the distance from the MS to the BS at time t = 1), provided that the matrix M given previously is invertable. If the matrix M cannot be inverted, additional MS positions and TOA measurements must be collected before the location can be accurately determined. Given x and y in terms of the distance variable d_1 (i.e., equation (6)), the distance variable d_1 can be substituted for the term $\sqrt{[(x - x_1)^2 + (y - y_1)^2]}$ to form a quadratic equation in terms of the distance variable d_1.

In a first method for obtaining a final solution, the quadratic equation for the distance variable d_1 is solved directly, producing two possible results for the distance variable d_1. This quadratic solution ambiguity can be resolved by discarding a solution that is out of the region of interest. The region of interest may be a position fix

5   determined by the mobile GPS receiver, or may be an indication of the serving cell location. In a second method for determining a final solution, the quadratic equation for the distance variable d_1 is solved by processing an additional TOA measurement, i.e., a fourth TOA measurement TOA_4 and a third difference TOA_4-TOA_1. The fourth TOA measurement TOA_4 leads to a third linear equation, similar in form to equations (11) and

10   (12). This permits a direct, unambiguous solution for x, y and d_1 (i.e., no approximate position knowledge is required). Either final solution method produces an estimated range d_e to the BS, which may be substituted into equation (6) to compute the BS coordinates x, y.

     In step 414, the perceived time bias offset b' is determined by subtracting the

15   estimated range d_e (i.e., the calculated distance determined above) from any of the TOA equations TOA_i. In step 416, the computed BS location and the perceived time bias offset b' are optimized in order to improve their accuracy and usefulness.

     The nonlinear solution for the BS coordinates x, y provides a starting point for calibrating the BS location in the MS. The calculated BS location, however, is capable of

20   being improved. The calibration may be fine-tuned by linearizing the TOA equations (1)-(3) and then computing a Weighted Least Squares (WLS) solution. The WLS solution will, in general, improve the accuracy of the calibration of the BS location and will enable a reasonable assessment of the accuracy of the calibration. This assessment can be used to determine when the BS location calibration is complete (i.e., satisfactorily accurate).

25   The TOA measurements (TOA_1, TOA_2, TOA_3) are linearized about the initial, nonlinear, solution by subtracting an estimated TOA (computed from the initial BS location with b' set to zero) from each measured TOA. Once linearized about the initial solution, the TOA measurement set (TOA_1, TOA_2 etc.) can be collected together as a vector of measurement residuals, TOA_{res}, defined as:

30
$$TOA_{res} = H\, x_{sol} \tag{13}$$

where H is a measurement gradient vector and x_{sol} is a three dimensional solution vector. Each row of H has the following general form:

$$h_i^T = [\, u_x\, u_y\, 1]$$

8

where u_x and u_y are the components of a Line Of Sight (LOS) unit vector to the BS (computed using its initial estimated location).

The WLS x_{sol} solution is given by:

$$x_{sol} = (H^T R^{-1} H)^{-1} H^T R^{-1} TOA_{res} \qquad (14)$$

5   where R is a measurement error covariance matrix corresponding to a TOA measurement set. Note that the R matrix must include the effects of the error in the GPS solution itself, projected along the estimated LOS unit vector to the BS.

A by-product of the WLS solution x_{sol} is the solution error covariance matrix $(H^T R^{-1} H)^{-1}$, which can and should be used to predict the accuracy of the calculated BS location

10   and the perceived time bias offset b'.

As previously mentioned, the calibration is complete when the solution error variances become acceptably small, and the error variances are confirmed by the residuals of an over-determined solution. A proposed acceptable solution error variance threshold is one meter, one sigma, which is negligible relative to the positioning

15   requirements (roughly fifty meters, one sigma, as specified in a U.S. Federal Communication Commission (FCC) edict on emergency positioning). As this requirement is relaxed, the required calibration accuracy can be relaxed proportionately.

Upon completion of the BS location calibration, subsequent TOA measurements can be combined with GPS pseudorange measurement data to improve the location

20   accuracy of the MS for calibrating other BS locations.

If the BS location is already known to the GPS receiver, but the perceived time bias offset b' is not, the problem is already in linear form and the solution is straightforward. The TOA residual vector is directly related to the time offset bias as:

$$TOA_{res} = H\,b_e \qquad (15)$$

25   Each row of H is unity and the perceived time bias offset b_e collapses to a weighted average of the measurement residuals. The accuracy of the perceived time bias offset b_e can be determined from the solution error covariance matrix $(H^T R^{-1} H)^{-1}$.

FIG. 5 shows a flowchart 500 of a second embodiment of a method for calibrating BS locations and perceved time bias offsets. In step 501, an MS collects TOA

30   measurements from a BS in a manner similar to the first flowchart 400, producing equations (1)-(3). In step 505, a corresponding number of GPS receiver position measurements are generated by the GPS receiver.

In step 506, the singular geometry of the TOA measurement set is again tested using the matrix M. As before, if the singularity of the received TOA measurements is inadequate, the method may acquire more TOA measurements and wait until the singularity reaches a certain threshold.

In step 508, the TOA measurements are used to create TOA difference equations (4) and (5). In step 511, the difference equations have the distance variable d_1 added to both side of the equation, the equations are squared, and the term d_1^2 is subtracted from both sides to yield equations (11) and (12). In step 514, the distance variable d_1 is substituted for the value $\sqrt{[(x - x_1)^2 + (y - y_1)^2]}$ to produce a quadratic equation in terms of the distance variable d_1.

In step 520, the distance variable d_1 is solved. In a first final solution method, the quadratic equation for the distance variable d_1 is solved directly, producing two possible results for the distance variable d_1. This quadratic solution ambiguity can be resolved by discarding a solution which is out of the region of interest. The region of interest may be a position fix determined by the mobile GPS receiver, or may be a set of previously acquired BS coordinates.

In a second final solution method, the quadratic equation for the distance variable d_1 is solved by processing a fourth TOA measurement TOA_4 and a third difference TOA_4-TOA_1. The third difference TOA_4-TOA_1 leads to a third linear equation, similar in form to equations (11) and (12). This permits a direct, unambiguous solution for x, y and d_1 (i.e., no approximate position knowledge is required).

In step 523, the computed BS coordinates x, y may be used to compute the perceived time bias offset b′. The perceived time bias offset b′ may be determined by subtracting the estimated range d_e from any of the TOA equations TOA_i. In step 527, the computed BS location and the perceived time bias offset b′ are optimized in the same manner as in the first flowchart 400.

Once the BS calibration is essentially complete, the perceived time bias offset b′ is periodically re-determined and associated with each MS location or BS service area. Over time, this association permits construction of a temporal map, or database, of perceived time bias offsets versus MS position over the area served by a BS. The perceived time bias offset may represent the time bias offset b as affected by spatial error from multipath in addition to the fixed error induced by cable delays, internal BS harnessing, software processing, clock source distribution, and other factors. This map can be

derived and maintained for many BSs by the cellular infrastructure and broadcast to other MSs (GPS of non-GPS equipped) to improve their location accuracy. Various other information can be appended to this map, such as a confidence factor based on a solution error variance, a time stamp based on ephemeris data, or the time bias offset b, for any

5   perceived time bias offset b'. Also the map may be compressed by reducing it merely to a correction factor of b.

The perceived time bias offset may be stored in MSs and subsequent offset measurements loaded periodically to a recording device in the infrastructure capable of creating the map. Alternatively, a simultaneous transaction session, such as a short

10   message service (SMS), Bluetooth, or a defined protocol, could act to transfer the perceived time bias offsets over the air back to the infrastructure or another MS, which may or may not be GPS assisted. The described perceived time bias offset calculation may be realized as a standard mode of operation requested by the infrastructure thereby allowing a population of MSs to participate in realizing the perceived time bias offset

15   map.

The perceived time bias offset map can be used in a variety of applications to aid in more accurate location of an MS, whether or not GPS-equipped. For example, typical multipath reduction techniques attempt to remove a calculated time bias offset based on a statistical measure of the variance of a signal over time. When line-of-sight (LOS)

20   conditions exist (i.e., there is little multipath), multipath reduction techniques end up compensating for a non-existent problem, and this "compensation" in effect adds error to the TOA estimate. To intelligently aid the effectiveness of such multipath reduction techniques, the realized map of perceived time bias offset versus position over the area served by each BS may be queried. The returned perceived time bias offset can be used

25   as a discriminator to determine when to use a multipath reduction technique.

Accessing precise perceived time bias offset map information could be obtained once a first GPS-based position is obtained. This precise value acts as a multipath reduction technique discriminator for BS TOA signals used in conjunction for subsequent hybrid GPS and cellular terrestrial position fixes. Alternatively, after a first

30   terrestrial-only (enhanced observed time difference (EOTD) or advanced forward-link trilateration (AFLT)) location fix is obtained via blindly applying a multipath rejection technique, the perceived time bias offset map values corresponding to the sum of the delays for each BS could be used in subsequent fixes as a location-specific reduction

value for terrestrial-only fixes. This application assumes an MS to also contain terrestrial location technology. The effect is to hone the terrestrial measurements over time.

Approximate perceived time bias offset information could be statistically generated for a cell or sector's service area. In rural cells, typical scenarios may incur low

5   amounts of multipath, in contrast to dense urban environments. This method allows the MS to decide if multipath rejection techniques should be executed. The lifetime of the specific perceived time bias offset value should ideally be re-evaluated upon each GPS position calculation opportunity that results in a BS calibration operation. GPS time, such as that found in ephemeris data, can be used to evaluate the "staleness" of the perceived

10   time bias offset value.

FIG. 6 shows a GPS receiver 600 that can be used for calibrating BS locations and perceived time bias offsets. The GPS receiver 600 includes an antenna 603, a GPS receiver component 608, a processor 613, and storage 620. The processor 613 may be any type of general purpose processor available in the art.

15   The storage 620 may be any type of storage memory, including random access memory (RAM), magnetic disk or tape, optical memory, etc. The storage 620 includes a TOA measurement storage 621 capable of storing a plurality of TOA measurements, a position fix storage 623 capable of storing a plurality of position fixes of the GPS receiver 600, a BS coordinates storage 626 capable of storing a calculated BS location and/or a BS

20   location received from the infrastructure, a time bias offset storage 628 capable of storing a calculated perceived time bias offset b' and/or a time bias offset b received from the infrastructure, an approximate location storage 631 capable of storing an approximate geographical location of the BS, a TOA residual vector storage 634 capable of storing a TOA residual vector formed from the TOA measurements, and a solution error variance

25   storage 636 capable of storing a solution error variance threshold.

It should be noted that although the individual components are shown as being dedicated components, alternatively the components may be shared with other hardware and functions. For example, when the GPS receiver 600 is combined with a cellular handset in an MS, the processor 613 and the storage 620 may be shared between

30   the cellular phone functionality and the GPS receiver functionality.

In use, a GPS signal is received through the antenna 603 and decoded by the GPS receiver component 608. The GPS receiver component 608 sends the decoded GPS data

to the processor 613, which may store some or all of the received GPS data in the storage 620.

The processor 613 is capable of collecting and storing TOA measurements, collecting and storing a corresponding number of GPS position measurements,

5   subtracting a first TOA measurement from subsequent TOA measurements to create TOA differences, substituting a distance variable d_1 for the unknown BS coordinates x, y in the TOA differences to produce a quadratic equation, solving the quadratic equation for the distance variable d_1 to obtain an estimated range d_e, solving for the unknown BS coordinates x, y, obtaining the perceived time bias offset b' by subtracting the estimated

10 range d_e from the TOA measurements, linearizing TOA equations to produce linearized TOA equations, generating a vector of measurement residuals TOA_{res}, computing a weighted least squares solution x_{sol} of the TOA equations, using the weighted least squares solution x_{sol} to assess an accuracy of the linearized TOA equations, and stopping the linearizing when solution error variances of the weighted least squares solution x_{sol}

15 become less than a solution error variance threshold. This solution error variance threshold can either be predetermined or calculated and modified dynamically.

In this manner, the GPS receiver 600 may operate autonomously and does not need to be dependent on reception of a BS location and time bias offset b. The BS location and perceived time bias offset b' derived by the GPS receiver 600 may be used in

20 conjunction with TOA measurements to accurately calculate a position fix of the GPS receiver 600.

While the invention has been described in detail above, the invention is not intended to be limited to the specific embodiments as described. For example, satellite positioning systems such as GLONASS can be substituted for the GPS satellite

25 positioning system. It is evident that those skilled in the art may now make numerous uses and modifications of and departures from the specific embodiments described herein without departing from the inventive concepts.

What is claimed is:

CLAIMS

1.   A method for calibrating a base station location using a satellite positioning receiver in a mobile station, characterized by the steps of:

collecting a number of time-of-arrival (TOA) measurements arriving at the mobile station from a base station;

5   simultaneously collecting a corresponding number of satellite position measurements of the satellite positioning receiver;

determining that the number of TOA measurements and the corresponding number of satellite position measurements is sufficient for calibrating the base station location; and

10   computing the base station location using the number of TOA measurements and the corresponding number of satellite position measurements.

2.   The method of claim 1, further characterized by the step of:

computing a perceived time bias offset b' using the number of TOA measurements and the corresponding number of satellite position measurements.

15 3.   The method of claim 2, further characterized by the steps of:

associating the perceived time bias offset b' with a satellite positioning receiver position; and

creating at least a portion of a map of perceived time bias offset as a function of satellite positioning receiver position.

20 4.   The method of claim 3, further characterized by the step of:

transmitting the map to another mobile station.

5.   The method of claim 3, wherein the step of creating comprised:

updating the map within a cellular infrastructure.

25 6.   The method of claim 5, further characterized by the step of:

using the perceived time bias offset in the map to determine whether to use a multipath reduction technique.

7.   The method of claim 6, further characterized by the step of:

using the perceived time bias offset in the map to compute a position of the

mobile station.

8.   The method of claim 1, wherein the step of computing comprises the steps of:

5   subtracting a first TOA measurement from subsequent TOA measurements to

create two TOA differences TOA_{31}, TOA_{21};

substituting a distance variable d_1 for base station coordinates x, y in the two TOA

differences TOA_{31}, TOA_{21} to produce a quadratic equation for the distance variable d_1,

where the distance variable $d_1 = \sqrt{[(x-x_t)^2 + (y-y_t)^2]}$;

10   solving the quadratic equation for the distance variable d_1 to obtain an estimated

range d_e; and

solving for the base station coordinates x, y using the estimated range d_e.

9.   The method of claim 8, further characterized by the step of:

computing a perceived time bias offset b' using the number of TOA

15   measurements and the corresponding number of satellite position measurements.

10.   The method of claim 9, wherein the step of computing a perceived time bias offset

b' comprises:

subtracting the estimated range d_e from a TOA measurement.

11.   A method for calibrating a base station location in a mobile station having a

20   satellite positioning receiver, characterized by the steps of:

collecting at least three TOA measurements TOA_1, TOA_2, TOA_3 arriving at the

mobile station from a base station at different times t, wherein a TOA measurement is

capable of being expressed as $TOA_t = b' + \sqrt{[(x - x_t)^2 + (y - y_t)^2]}$, with variable b' being a

perceived time bias offset of the base station and (x, y) being base station coordinates;

25   simultaneously collecting at least three satellite position measurements of a

position of the satellite positioning receiver, wherein a position measurement is denoted

as x_t and y_t as a function of time;

determining through a geometry matrix that the at least three TOA measurements and the at least three satellite position measurements are sufficient for determining the base station location;

subtracting a first TOA measurement TOA_1 from at least two subsequent TOA
5   measurements TOA_2, TOA_3 to create at least two TOA differences TOA_{31}, TOA_{21};

substituting a distance variable d_1 for the base station coordinates x, y in the at least two TOA differences TOA_{31}, TOA_{21} to produce a quadratic equation for the distance variable d_1, where the distance variable $d_1 = \sqrt{[(x-x_i)^2 + (y-y_i)^2]}$;

solving the quadratic equation for the distance variable d_1 to obtain an estimated
10   range d_e;

solving for the base station coordinates x, y using the estimated range d_e; and

obtaining the perceived time bias offset b' by subtracting the estimated range d_e from a TOA measurement.

12.   The method of claim 11, wherein the step of solving the quadratic equation
15   comprises the steps of:

solving the quadratic equation to produce two solutions; and

discarding a solution that is out of a geographical region of interest to leave an accepted solution.

13.   The method of claim 11, wherein the step of solving the quadratic equation
20   comprises the steps of:

obtaining at least a fourth TOA measurement and at least a third TOA difference; and

using the at least a third TOA difference in conjunction with the quadratic equation to determine a solution for the distance variable d_1 and for the base station
25   coordinates x, y.

14.   The method of claim 11, further including the steps of:

linearizing the at least three TOA measurements TOA_1, TOA_2, TOA_3 by subtracting estimated ranges from them, with the estimated ranges determined from the base station coordinates x, y, to produce linearized TOA equations;

30   generating a vector of measurement residuals TOA_{res};

16

computing a weighted least squares solution x_{sol} of the linearized TOA equations;

correcting the base station coordinates x, y using the weighted least squares solution x_{sol};

repeating the steps of generating, computing, and correcting until a magnitude of

5   the weighted least squares solution x_{sol} becomes less than a solution error variance threshold;

using a covariance matrix of the weighted least squares solution x_{sol} to assess an accuracy of the base station coordinates x, y; and

using the accuracy to determine that the base station location calibration is

10   complete.

15.   The method of claim 14, wherein the step of using the covariance matrix additionally makes use of measurement residual information from the weighted least squares solution x_{sol}.

16.   The method of claim 14, wherein the step of using the accuracy additionally

15   makes use of residual information from the weighted least squares solution x_{sol}.

17.   The method of claim 14, wherein the vector of measurement residuals TOA_{res} is given by $TOA_{res} = H\, x_{sol}$, where H is a measurement gradient vector and the weighted least squares solution x_{sol} is a three dimensional weighted least squares solution vector, and where a row of the measurement gradient vector H has a form of $h_i^T = [\, u_x\ u_y\ 1]$ with

20   u_x and u_y being components of a line of sight unit vector to the base station.

18.   The method of claim 14, wherein the weighted least squares solution x_{sol} is given as $x_{sol} = (H^T R^{-1} H)^{-1} H^T R^{-1} TOA_{res}$, where R is the covariance matrix.

19.   The method of claim 14, wherein if the base station coordinates x, y are known but the perceived time bias offset b' is not known, then a TOA residual vector TOA_{res} is given

25   by $TOA_{res} = H\, b_e$, where each row of H is unity and an estimated time bias offset b_e collapses to a weighted average of measurement residuals, and an accuracy of the estimated time bias offset b_e can be determined from the covariance matrix.

20.   An apparatus for calibrating a base station location in a mobile station, characterized by:

a satellite positioning receiver;

a radio transceiver;

5   a time-of-arrival (TOA) measurement storage for storing a plurality of TOA measurements;

a satellite positioning receiver position fix storage for storing a plurality of position fixes;

a base station coordinates storage;

10   a time bias offset storage; and

a processor, for communicating with the radio transceiver and satellite positioning receiver to receive signals from satellite positioning satellites and from a base station, and further communicating with the TOA measurement storage, the satellite positioning receiver position fix storage, the base station coordinates storage, and the

15   time bias offset storage, with the processor capable of collecting and storing TOA measurements, collecting and storing a corresponding number of satellite position measurements, subtracting a first TOA measurement from subsequent TOA measurements to create TOA differences, substituting a distance variable d_1 for base station coordinates x, y in the TOA differences to produce a quadratic equation, solving

20   the quadratic equation for the distance variable d_1 to obtain an estimated range d_e, solving for the base station coordinates x, y, obtaining a perceived time bias offset b' by subtracting an estimated range d_e from the TOA measurements, linearizing the TOA measurements to produce linearized TOA equations, generating a vector of measurement residuals TOA_{res}, computing a weighted least squares solution x_{sol} of the

25   linearized TOA equations, using the weighted least squares solution x_{sol} to assess an accuracy of the linearized TOA equations, and repeating the generating, computing, and using until a solution error variance of the weighted least squares solution x_{sol} becomes less than a solution error variance threshold.

21.   The apparatus of claim 20, further including an approximate geographical

30   location storage, communicating with the processor, for storing an approximate geographical location for use in obtaining an estimated range d_e.

22.   The apparatus of claim 20, further including a TOA residual vector storage, communicating with the processor, for holding the vector of measurement residuals TOA_{res}.

23.   The apparatus of claim 20, further including a solution error variance threshold
5   storage, communicating with the processor, for holding the solution error variance threshold.

24.   A map characterized by:
       a perceived time bias offset as seen by a mobile station as a function of a computed satellite positioning receiver position.

10   25.   A map according to claim 24 further characterized by:
              a confidence factor associated with the perceived time bias offset.

26.   A map according to claim 24 further characterized by:
   a time stamp associated with the perceived time bias offset.

27.   A map according to claim 24 further characterized by:
15   a time bias offset associated with the perceived time bias offset.

RECEIVER
B

RECEIVER
A

RECEIVER
C

BASE
STATION

X_{BS}, Y_{BS}

—PRIOR ART—

FIG. 1

BS

$y_1 - y_0$

d_1

MS

$x_1 - x_0$

FIG. 2

$X_2 Y_2$

MS$_2$

MS$_1$

$X_1 Y_1$

d_2

MS$_3$

$X_3 Y_3$

d_1

d_3

BASE
STATION

X Y

FIG. 3

FIG. 4

FIG. 6

FIG. 5

INTERNATIONAL SEARCH REPORT

A. CLASSIFICATION OF SUBJECT MATTER

IPC(7)   :   G01S 5/02; H04B 7/185

US CL   :   342/357.06; 455/456; 701/214

According to International Patent Classification (IPC) or to both national classification and IPC

B. FIELDS SEARCHED

Minimum documentation searched (classification system followed by classification symbols)

U.S. : 342/357.06, 357.01, 357.08, 357.1, 357.13; 455/456, 457; 701/214, 213

Documentation searched other than minimum documentation to the extent that such documents are included in the fields searched

None

Electronic data base consulted during the international search (name of data base and, where practicable, search terms used)

None

C. DOCUMENTS CONSIDERED TO BE RELEVANT

Category *	Citation of document, with indication, where appropriate, of the relevant passages	Relevant to claim No.
X	US 5,986,603 A (SCHIPPER) 16 November 1999 (16.11.1999), figures 6-7, column 19 lines 33-64.	24-27
X,P	US 6,252,543 B1 (CAMP) 26 June 2001 (26.06.2001), column 13 line 10 to column 14 line 35.	24-27

☐ Further documents are listed in the continuation of Box C.   ☐ See patent family annex.

*	Special categories of cited documents:	"T"	later document published after the international filing date or priority date and not in conflict with the application but cited to understand the principle or theory underlying the invention
"A"	document defining the general state of the art which is not considered to be of particular relevance		
"B"	earlier application or patent published on or after the international filing date	"X"	document of particular relevance; the claimed invention cannot be considered novel or cannot be considered to involve an inventive step when the document is taken alone
"L"	document which may throw doubts on priority claim(s) or which is cited to establish the publication date of another citation or other special reason (as specified)	"Y"	document of particular relevance; the claimed invention cannot be considered to involve an inventive step when the document is combined with one or more other such documents, such combination being obvious to a person skilled in the art
"O"	document referring to an oral disclosure, use, exhibition or other means	"&"	document member of the same patent family
"P"	document published prior to the international filing date but later than the priority date claimed		

Date of the actual completion of the international search	Date of mailing of the international search report
13 November 2001 (13.11.2001)	2 7 DEC 2001

Name and mailing address of the ISA/US	Authorized officer
Commissioner of Patents and Trademarks Box PCT Washington, D.C. 20231 Facsimile No. (703)305-3230	Nguyen T Vo Telephone No. (703) 305-3900

Form PCT/ISA/210 (second sheet) (July 1998)

Continuation of Item 4 of the first sheet:
The title is beyond 17 word limit. A new title is suggested below:
METHOD AND APPARATUS FOR CALIBRATING BASE STATION LOCATIONS AND PERCEIVED TIME BIAS OFFSETS.